

ASR-6000 Series

High-Performance AC/DC Power Supply



FEATURES

- * Adopts Third-generation Semiconductor Silicon Carbide (SiC) Technology to Create a 4U 6kVA High-performance AC/DC Power Source with High Power Density
- * AC Input Supports Single-phase and Three-phase, Phase Voltage 200V to 240V $\pm$ 10% (Delta or Y Connection)
- * 10 output Modes: Including External Input Signal Frequency and Mains Synchronization(SYNC), External Voltage Controlled Internal Amplifier Output (VCA)
- * Multi-channel Output Function
- * Supports AC 1P2W, 1P3W, 3P4W Output
- * AC Maximum Output Phase Voltage: 350Vrms Line Voltage: 700Vrms
- * AC Balanced and Unbalanced Three-phase, Phase Failure Output Functions
- * Programmable Output Impedance Adjustment
- * Dual-channel Voltage/current Output Monitoring Function
- * Voltage Output Rise Time Can be Adjusted in Three Ranges
- * Supports Sequence Editing and Emulation Output Mode
- * Powerful Arbitrary Waveform Editing and Output Function, Built-in Over 40 Types of Arbitrary Waveform Outputs
- * Advanced Web Server Control to Support Data Acquisition and Data Logger Both Functions
- * 100th Order Harmonic Measurement Function
- * Support External Parallel Connection to Increase Output Power
- * Support Diverse Interface: RS-232C(Std), USB(Std), LAN(Std), CAN BUS(Opt), DeviceNet(Opt), GPIB(Opt)

APPLICATIONS

- * Server/Communication Power Supply
- * 6kVA Car Charger
- * Uninterruptible Power Supply System (UPS)
- * Military Industry, Scientific Research, Education
- * AC Inverter
- * AC Motor Controllers and Protection Devices

From the very moment Alpha Go defeated the human chess champion with its ultra-high-speed computing capability, artificial intelligence technology (AI) has developed rapidly around the world. Today, servers with advanced AI functions process tremendous amounts of data under the high-speed computing architecture of 2 CPUs + 8 GPUs. servers require a huge amount of power to maintain high-speed computing! In order to meet this demand, the power, density and efficiency of server power supplies have been greatly improved. High-power server power modules require high-efficiency conversion and saving of power consumption. AC single-phase input, HVDC 400V input or increased DC voltage output designs can be utilized to achieve this purpose. In order to ensure power stability when high-power servers are operating, power modules with hot-swappable redundant power supply specifications (such as CRPS) have been widely applied in server racks. Power modules with redundant functions require testing of multiple power modules at a time to ensure that all modules can maintain normal operation during high power output. Due to the rapid changes in the development of server power supplies GW Instek developed the brand new flagship model ASR-6000 series to meet customer needs. ASR-6000 series series has two models - ASR-6450 AC/DC 4.5kVA and ASR-6600 series AC/DC 6kVA.

ASR-6000 series is the first stand-alone unit from GW Instek that supports AC single/three-phase input and output, and has rated DC power output. The series employs third-generation semiconductor silicon carbide (SiC) technology to create a 4U 6kVA high power density and high-performance AC/DC power source ASR-6000 series has the ability to emulate more diverse power environment changes, such as balanced three-phase and unbalanced three-phase, phase failure, and features multi-channel output function in three-phase output mode, programmable output impedance adjustment, and up to tens of thousands of arbitrary waveform outputs. The invincible launch of GW Instek flagship model ASR-6000 series demonstrates that GW Instek can provide a complete test solution for high-power AC sources. ASR-6000 series is the MVP of GW Instek power sources.

Model	ASR-6450	ASR-6600
AC Input Voltage	Single/Three Phase 200 Vac to 240 Vac $\pm$ 10 %	
AC Output Voltage	Phase Voltage 0~175V/0~300V Line Voltage 0~700V	
AC Output Current	1P2W 45A/22.5A;1P3W & 3P4W;15A/7.5A	1P2W 60A/30A;1P3W & 3P4W;20A/10A
Output Frequency	2000Hz	2000Hz
Rated Output Power	1P2W~4.5KVA;1P3W~3KVA;3P4W~4.5KVA	1P2W~6KVA;1P3W~4KVA;3P4W~6KVA
DC Output Voltage	-250.0 V ~ +250.0 V/-500.0 V ~ +500.0 V	



Website



Facebook



LinkedIn

SPECIFICATIONS					
Model		ASR-6450		ASR-6600	
Input Ratings					
Power type		Single-phase ; Three-phase, Delta or Y connection selectable			
Voltage range ^{*1}		200 Vac to 240 Vac ±10 % phase voltage (Delta: L-L, Y: L-N)			
Frequency range		47 Hz to 63 Hz			
Power factor ^{*2}		0.95 or higher (typ.)			
Efficiency ^{*2}		80 % or higher			
Maximum power consumption		6 kVA or lower		8 kVA or lower	
AC Output					
Multi-phase output		Single-phase output		Polyphase output	
Output capacity		4.5 kVA		6 kVA	
Mode		1P2W		1P3W ; 3P4W (Y-connection)	
Setting mode ^{*3}		---		Independ, Balanced	
Phase voltage		0.00 V to 175.0 V / 0.0 V to 350.0 V (sine and square wave), Setting Resolution: 0.01 V / 0.1 V			
		0.00 Vpp to 500.0 Vpp / 0.00 Vpp to 1000 Vpp (triangle and arbitrary wave), Setting Resolution: 0.01 Vpp / 0.1 Vpp / 1 Vpp			
		±(0.3 % of set + 0.5 V / 1 V)			
Line voltage setting range ^{*6}		---		---	
		1P3W: 0.00 V to 350.0 V / 0.00 V to 700.0 V 3P4W: 0.00 V to 303.1 V / 0.00 V to 606.2 V (sine and square wave) Setting Resolution: 0.01 V / 0.1 V		1P3W: 0.00 V to 350.0 V / 0.00 V to 700.0 V 3P4W: 0.00 V to 303.1 V / 0.00 V to 606.2 V (sine and square wave) Setting Resolution: 0.01 V / 0.1 V	
Maximum current ^{*7}		45 A / 22.5 A		60 A / 30 A	
		15 A / 7.5 A		20 A / 10 A	
Maximum peak current ^{*8}		Four times of the maximum RMS current			
Load power factor ^{*9}		0 to 1 (leading phase or lagging phase, 45 Hz to 65Hz)			
Frequency		AC Mode: 15.00 Hz to 2000.0 Hz, AC+DC Mode: 1.00 Hz to 2000.0 Hz, Setting resolution: 0.01 Hz / 0.1 Hz			
		Accuracy			
		Stability ^{*10}			
Output on phase setting range ^{*11}		0.0° to 359.9° variable (Free / Fix selectable), 0.1° (1 Hz to 500 Hz), 1° (500 Hz to 2000 Hz)			
Output off phase setting range ^{*11}		0.0° to 359.9° variable (Free / Fix selectable), 0.1° (1 Hz to 500 Hz), 1° (500 Hz to 2000 Hz)			
Setting range of the phase angle ^{*12}		---		---	
Phase angle accuracy ^{*13}		---		---	
DC offset ^{*14}		± 20 mV (typ.)			
DC Output (Only Single Phase Output)					
Output capacity		4.5 kW		6 kW	
Mode		Floating output, the N terminal can be grounded			
Voltage		Setting Range			
		Accuracy ^{*15}			
Maximum current ^{*16}		45 A / 22.5 A		60 A / 30 A	
Maximum peak current ^{*17}		Four times of the maximum current			
Output Stability, Total Harmonic Distortion, Output Voltage Rising Time and Ripple Noise					
Line regulation		±0.1% or less (Phase voltage)			
Load regulation ^{*18}		±0.1 V / ±0.2 V, @DC (only single-phase output)			
		±0.1 V / ±0.2 V, @45 Hz to 65 Hz (phase voltage, 0 to 100%, via output terminal)			
		±0.5 V / ±1.0 V, @all other frequencies (phase voltage, 0 to 100%, via output terminal)			
Distortion of Output ^{*19}		<0.3 % @1Hz to 100Hz, <0.5 % @100.1 Hz to 500 Hz, <1 % @500.1 Hz to 2000 Hz			
Output voltage response time ^{*20}		Fast: 50 μs (typ.) ; Middle:100μs (typ.) ; Slow: 300 μs (typ.)			
Ripple noise ^{*21}		0.5 Vrms / 1 Vrms (TYP)			
*1 Y connection is three-phase, five-wire, Delta connection is three-phase, four-wire. (Accessories will be provided)					
*2. In the case of AC+INT mode, the rate output voltage, resistance load at maximum output current,45 Hz to 65 Hz and sine wave output only.					
*3. Can be only set in polyphase mode.					
*4. For phase voltage setting in polyphase output. In balance mode all phase are collectively set and in unbalance mode each phase are individually set.					
*5. For an output voltage of 10 V to 175 V / 20 V to 350 V, sine wave, an output frequency of 45 Hz to 65 Hz, no load, DC voltage setting 0V (AC+DC mode) and 23°C ± 5°C. For phase voltage setting in the polyphase output.					
*6. Line voltage only can be set in balance mode.					
*7. If the output voltage is higher than rated value, this is limited to satisfy the power capacity. If there is the DC superimpositions, the active current of AC+DC satisfies the maximum current. In the case of 40 Hz or lower or 400 Hz or higher, and that the ambient temperature is 40 degree or higher, the maximum current may decrease.					
*8. With respect to the capacitor-input rectifying load. Limited by the maximum current.					
*9. External power injection or regeneration which is over short reverse power flow capacity is not available.					
*16. If the output voltage is higher than rated value, this is limited to satisfy the power capacity. If there is the AC superimpositions , the active current of AC+DC satisfies the maximum current. And the ambient temperature is 40 degree or higher, the maximum current may decrease.					
*17. Instantaneous within 3 ms , limited by the maximum current at rated output voltage.					
*18. For an output voltage of 75 V to 175 V / 150 V to 350 V, a load power factor of 1,stepwise change from an output current of 0 A to maximum current (or its reverse), using the output terminal on the rear panel.					
*19. 50 % or higher of the rated output voltage, the maximum current or lower, AC and AC+DC modes, THD+N. For the polyphase it is a specification for phase voltage setting.					
*20. For an output voltage of 100 V / 200 V, a load power factor of 1, with respect to stepwise change from an output current of 0 A to the maximum current (or its reverse). 10% ~ 90% of output voltage.					
*21. For 5 Hz to 1 MHz components in DC mode using the output terminal on the rear panel.					
Measured Value Display (All accuracy of the measurement function is indicated for 23 °C±5 °C.)					
Voltage ^{*1*2}		Single-phase output		Polyphase output ^{*6}	
		Resolution		0.01 V / 0.1 V	
		RMS value accuracy		45 Hz to 65 Hz and DC: ± (0.5 % of rdg + 0.5 V / 1 V) 15 Hz to 2000 Hz: ± (0.7 % of rdg + 1 V / 2 V)	
		AVG value accuracy		DC: ± ([0.5 % of rdg] + 0.5 V / 1 V)	
		PEAK value accuracy ^{*3}		45 Hz to 65 Hz and DC: ±([2 % of rdg] + 1 V / 2 V)	
Current ^{*4}		Resolution		0.01 A / 0.1 A	
		RMS value accuracy		45 Hz to 65 Hz and DC: ±(0.5 % of rdg + 0.1 A / 0.05 A) 15 Hz to 2000 Hz: ±(0.7 % of rdg + 0.2 A / 0.1 A)	
		AVG value accuracy		DC: ± ([0.5 % of rdg] + 0.2 A / 0.1 A)	
		PEAK value accuracy ^{*5}		45 Hz to 65 Hz and DC: ±([2 % of rdg] + 1 A / 0.5 A)	
				45 Hz to 65 Hz: ±([2 % of rdg] + 0.5 A / 0.25 A)	

SPECIFICATIONS				
Model			ASR-6450	ASR-6600
Power ^{*7*8}	Active (W)	Resolution	0.1 W / 1 W	
		Accuracy ^{*9}	±(1 % of rdg + 3 W)	±(1 % of rdg + 1 W)
	Apparent (VA)	Resolution	0.1 VA / 1 VA	
		Accuracy	±(2 % of rdg + 6 VA)	±(2 % of rdg + 2 VA)
	Reactive (VAR)	Resolution	0.1 VAR / 1 VAR	
		Accuracy ^{*10}	±(2 % of rdg + 6 VAR)	±(2 % of rdg + 2 VAR)
Power factor		Range	0.000 to 1.000	
		Resolution	0.001	
Harmonic voltage Effective value (rms) Percent (%) (AC-INT and 50/60 Hz only) ^{*11}		Range	Up to 100th order of the fundamental wave	
		Full Scale	200 V / 400 V, 100%	
		Resolution	0.01 V / 0.1 V, 0.1%	
		Accuracy ^{*12}	Up to 20th: ±(0.2 % of rdg + 0.5 V / 1 V) ; 20th to 100th: ±(0.3 % of rdg + 0.5 V / 1 V)	
Harmonic current Effective value (rms) Percent (%) (AC-INT and 50/60 Hz only) ^{*11}		Range	Up to 100th order of the fundamental wave	
		Full Scale	63 A / 31.5 A, 100%	21 A / 10.5 A, 100%
		Resolution	0.01 A / 0.1 A, 0.1%	
		Accuracy ^{*13}	Up to 20th: ±(1 % of rdg + 1.5 A / 0.75 A) 20th to 100th: ±(1.5 % of rdg + 1.5 A / 0.75 A)	Up to 20th: ±(1 % of rdg + 0.5 A / 0.25 A) 20th to 100th: ±(1.5 % of rdg + 0.5 A / 0.25 A)
*1. In the polyphase output, the specification is for phase voltage, and the DC average value display cannot be selected. *2. Accuracy values are in the case that the output voltage is within voltage setting range. *3. The accuracy is for output waveform DC or sine wave only. *4. Accuracy values are in the case that the output current is 5% to 100% of the maximum current. *5. The accuracy is for output waveform DC or sine wave only. *6. In the polyphase output, these are the specifications for each phase. *7. For an output voltage of 50 V or greater, an output current in the range of 10 % to 100 % of the maximum current, DC or an output frequency of 45 Hz to 65 Hz. *8. The apparent and reactive powers are not displayed in the DC mode. *9. For the load with the power factor 0.5 or higher. *10. For the load with the power factor 0.5 or lower. *11. The measurement does not conform to the IEC or other standard. Phase Voltage and Phase Current. *12. For an output voltage of 10 V to 175 V / 20 V to 350 V. *13. An output current in the range of 5 % to 100 % of the maximum current.				
Others				
Protections		UVP, OVP, OCP, OTP, OPP, Fan Fail, Peak and RMS Current Limit		
Parallel function		Up to 3 units		
Display		TFT-LCD, 7 inch		
Memory function		Store and recall settings, Basic settings: 10		
Arbitrary Wave	Number of memories	16 (nonvolatile)		
	Waveform length	4096 words		
	Amplitude resolution	16 bits		
General Specifications				
Interface	Standard	USB	Type A: Host, Type B: Slave, Speed: 1.1/2.0, USB-CDC / USB-TMC	
		LAN	MAC Address, DNS IP Address, User Password, Gateway IP Address, Instrument IP Address, Subnet Mask	
		External	External Signal Input ; External Control I/O ; V/I Monitor Output	
		RS-232C	Complies with the EIA-RS-232 specifications	
	Optional 1	GPIO	SCPI-1993, IEEE 488.2 compliant interface	
	Optional 2	CAN Bus	Complies with CAN 2.0A or 2.0B based protocol	
Optional 3	DeviceNet	Complies with CAN 2.0A or 2.0B based protocol		
Insulation resistance	Between input and chassis, output and chassis, input and output	DC 500 V, 30 MΩ or more		
Withstand voltage	Between input and chassis, output and chassis, input and output	AC 1500 V or DC 2130 V , 1 minute		
EMC		EN 61326-1 (Class A) EN 61326-2-1/-2-2 (Class A) EN 61000-3-2/-3-12 (Class A, Group 1) EN 61000-3-3/-3-11 (Class A, Group 1) EN 61000-4-2/-4-3/-4-4/-4-5/-4-6/-4-8/-4-11/-4-34 (Class A, Group 1) EN 55011 (Class A, Group1)		
Safety		EN 61010-1		
Vibration, Shock and Transportation Integrity		ISTA 2A Test Procedure		
Environment	Operating environment		Indoor use, Overvoltage Category II	
	Operating temperature range		0 °C to 40 °C	
	Storage temperature range		-10 °C to 70 °C	
	Operating humidity range		20 %rh to 80 % RH (no condensation)	
	Storage humidity range		90 % RH or less (no condensation)	
	Altitude		Up to 2000 m	
Dimensions (mm)		430(W)×176(H)×590(D) (not including protrusions)		
Weight		Approx. 40 kg		
A value with the accuracy is the guaranteed value of the specification. However, an accuracy noted as reference value shows the supplemental data for reference when the product is used, and is not under the guarantee. A value without the accuracy is the nominal value or representative value (shown as typ.). Product specifications are subject to change without notice.				

Specifications subject to change without notice. ASR-6000ID1DS

ORDERING INFORMATION	
ASR-6450	4.5kVA High-Performance AC/DC Power Supply
ASR-6600	6kVA High-Performance AC/DC Power Supply
ACCESSORIES	
Quick start guide, Safety guide, Input terminal cover, Output terminal cover, Copper plate for delta connection input, Copper plate for single phase and Y connection input, Copper plate for delta connection input, Copper plate for 1P output, GRA-451-E Rack mount adapter (EIA) GTL-246 USB cable (USB 2.0 Type A - Type B cable, approx. 1.2M)	

OPTION ACCESSORIES			
ASR-003	GPIO interface card	GTL-232	RS-232C Cable, approx. 2M
ASR-004	DeviceNet interface card	GTL-248	GPIO Cable, approx. 2M
ASR-005	CAN BUS interface card	GRA-451-E	Rack mount adapter (EIA)
ASR-006	External parallel cable	GRA-451-J	Rack mount adapter (IIS)
GPW-008	6RV3 Power Cord; 10AWG/3C, 3m Max Length, , RV5-5*3P, RV5-5*3P UL TYPE		
GPW-009	6RVV3 Power Cord; 2.5mm2/3C, 3m Max Length,, RV5-5*3P, RV5-5*3P VDE TYPE		
GPW-010	6RVT3 Power Cord; 2.0mm2/3C, 3m Max Length, RV5-5*3P, RV5-5*3P PSE TYPE		
GPW-011	6RV5 UL Power Cord; 10AWG/5C, 3m, RV5-5*5P, RV5-5*5P UL Type		
GPW-012	6RVV5 VDE Power Cord; 2.5mm2/5C, 3m Max Length, RV5-5*5P, RV5-5*5P VDE Type		
GPW-013	6RVT5 PSE Power Cord; 2.0mm2/5C, 3m Max Length, RV5-5*5P, RV5-5*5P PSE Type		
GPW-014	6RV4 UL Power Cord; 10AWG/4C, 3m, RV5-5*4P, RV5-5*4P UL TYPE		
GPW-015	6RVV4 VDE Power Cord; 2.5mm2/4C, 3m Max Length, RV5-5*4P, RV5-5*4P VDE Type		
GPW-016	6RVT4 PSE Power Cord; 2.0mm2/4C, 3m Max Length, RV5-5*4P, RV5-5*4P PSE Type		

GOOD WILL INSTRUMENT CO., LTD.

No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan
 T +886-2-2268-0389 F +886-2-2268-0639
 E-mail: marketing@goodwill.com.tw

GW INSTEK
 Simply Reliable